

Volume

1

QUANTUM SCIENTIFIC IMAGING

500 Series CCD Imaging Cameras

**COM API
Reference v4.5**

WINDOWS® OPERATING SYSTEMS

API Reference Manual

© Quantum Scientific Imaging, Inc.
34145 Pacific Coast Highway • Suite 512
Dana Point, CA 92629
Phone 888.774.4223 • Fax 888.774.4223

Disclaimer:

Quantum Scientific Imaging, Inc. assumes no liability for the use of the information contained in this document or the software for which it describes. The user assumes all risks. There is no warranty of fitness for a particular purpose, either express or implied.

The information contained in this document is assumed to be correct, but in no event shall Quantum Scientific Imaging, Inc. be held responsible for typographic errors or changes to the software not reflected in this document.


The specifications in this document are subject to change without notice.

Support:

The QSI API development specification is provided as a courtesy to our customers, and comes without warranty of fitness for any purpose or application, either express or implied. The user assumes all risk for the use of the information in this document and the software it describes.

Copyright 2006, 2007, 2008 Quantum Scientific Imaging, Inc.
All rights reserved.

All trademarks mentioned in this document are the property of their respective owners, and are used herein solely for informational purposes only.



Introduction

Using the QSI COM API to control your QSI camera

The QSI COM API provides a programming interface on Windows platforms to capture images and control QSI cameras. Any COM compliant programming language can be used. These languages include Microsoft VB.net, VBA, VBScript, C#, C++.

The QSI API is compliant with the ASCOM interface definitions for camera and filter wheels. The API includes methods and properties beyond the ASCOM standard to fully expose the capabilities of the QSI camera.

The QSI API COM library exposes the ICameraEx, ICamera, IFilterWheelEx and IFilterWheel interfaces. Each interface is composed of method calls and properties. A method call is made by the application to perform an action, such as start an exposure. A property is information about the camera that can be retrieved or set to a new value. An example of a property is the temperature set point of the ccd cooler, SetCCDtemperature. When this value is read by the program, the API returns the current setting of the cooler. When this value is written to, a new cooler set point is assigned.

The COM server that implements the API is included on the standard QSI installation disc in the form of a Windows® dll and is automatically installed when the QSI device drivers are installed on the target system. The QSI API COM object CCDcamera is implemented in the QSICamera.dll file located in the QSI installation directory, typically C:\Program Files\QSI. If you wish to manually install this dll, follow these instructions:

```
Open a command window (>Start>Run, cmd, OK)
Navigate to the directory where the QSICamera.dll resides.
Execute the following command:
Regsvr32.exe QSICamera.dll
Close the dialog that confirms the registration.
Close the command window.
```

How to Use the QSI Camera COM object

You must first install the QSI Camera software and drivers using the QSI Installation CD-ROM the came with your camera. The QSI installer is also available for download at <http://www.qsimaging.com/support/downloads.html>.

The ProgID is the standard way a program locates a COM object using the registry on Windows® systems. The ProgID for the QSI API is QSIcameraLib.CCDCamera.

When using Visual Studio and .net languages, a reference to the "ASCOM Camera Driver for QSI" COM component should be added to your project and you should include the QSIcameraLib in your source:

VB:

```
Imports QSIcameraLib
```

C#

```
using QSIcameraLib;
```

You must also create an instance of the QSI CCDCamera class for each camera you wish to control:

VB:

```
Private cam As QSIcameraLib.CCDCameraClass  
cam = New CCDCameraClass()
```

C#

```
QSIcameraLib.CCDCameraClass cam;  
cam = new CCDCameraClass();
```

You are now ready to start implementing you camera control program.

CCD Camera Supporting Information

CCD Imager Geometry

The CCD imager geometry is organized in rows and columns. The number of columns is the number of pixels in the image in the X (horizontal) direction, starting from the left of the image. The number of rows is the number of pixels in the Y (vertical) direction, starting at the top.

API REFERENCE

The API provides the total number of columns as the property `CameraXSize` and the total number of rows as the property `CameraYSize`. These properties are valid only when the camera is in the connected state.

The frame to be captured is defined by four properties, `StartX`, `StartY`, which define the upperleft corner of the frame, and `NumX` and `NumY` the define the binned size of the frame.

Pixel binning combines CCD pixels into groups with each group representing one image pixel.

Restrictions on binning are:

The properties `BinX` and `BinY` specify the number of bits per bin for each axis. If `CanAsymmetricBin` is `False`, `BinX` must equal `BinY`.

`MaxXBin` and `MaxYBin` specify the maximum number of bits per bin allowed by the camera for each axis. Therefore, $\text{BinX} \leq \text{MaxXBin}$ and $\text{BinY} \leq \text{MaxYBin}$.

The total number of bits in a image frame must not exceed the CCD dimension. Therefore, $(\text{StartX} + \text{NumX}) * \text{BinX} \leq \text{CameraXSize}$ and $(\text{StartY} + \text{NumY}) * \text{BinY} \leq \text{CameraYSize}$

Shutterless Cameras

The second parameter in `StartExposure(Duration, Light)` determines the shutter state during exposure. If the `Light` argument is `True`, the shutter is opened during the exposure period. If the property `HasShutter` is `False`, the `Light` parameter is ignored and the shutter is always in the open state.

Camera with Filter Wheels

Some QSI camera models contain an integral filter wheel. The property `HasFilterWheel` will return `True` if the camera contains a internal filter wheel. This property will return `False` if the camera has no internal wheel and is not affected by the existence of an external filter wheel. If you have an external filter wheel, use the ASCOM driver provided by the filter wheel manufacturer to control the wheel.

Image copy efficiency

The API provides three properties to retrieve image data: `ImageArray`, `ImageArrayVariant`, `ImageArrayLong`.

`ImageArrayLong` returns a `SAFEARRAY` of long values. This is the most efficient and preferred way to return the image data. It avoids the large per value memory overhead of a `Variant` type. This method is not part of the ASCOM specification, ASCOM users should use `ImageArray` or `ImageArrayVariant`.

`ImageArray` returns a `Variant` with a vartype of `SAFEARRAY long` as per the ASCOM v5 specification.

API REFERENCE

Unfortunately, the SAFEARRAY long data type is not available to simple scripting languages, such as VBScript. In this case, use ImageArrayVariant, which returns a VARIANT of varitype SAFEARRAY of Variants.

ASCOM notes

The ASCOM interface specification states that if a property or method is not supported or the object encounters an error in execution, the API will throw an exception. This is required because there is no provision for a property or method to return an error code. The calling application should wrap calls to the properties/methods that can throw an exception with a try/catch block.

For example:

VB:

```
Dim eGain as Double
Try
    eGain = cam.ElectronsPerADU
Catch [error] As Exception
    Console.WriteLine([error].ToString())
End Try
```

C#:

```
double eGain;
try
{
    eGain = cam.ElectronsPerADU;
}
catch (Exception error)
{
    Console.WriteLine(error.ToString());
}
```

ASCOM specifies a separate COM interface for the Filter Wheel. The QSI.Camera.CCDCCamera class implements both the ICamera and IFilterWheel interfaces. The IFilterWheel interface is only usable when the camera contains an internal filter wheel. The ICamera property HasFilterWheel will return true if the connected camera has an internal filter wheel.

The IFilterWheel properties and methods have been included in the ICamera interface for convenience. However, there is one property name and one method name that are defined in both interfaces: the property Connected and the method SetupDialog(). Fortunately, the Connected property and the SetupDialog method perform the same function for both ICamera and IFilterWheel, as the filter wheel is contained in the camera. If you wish to explicitly access the filter wheel property and method there are two ways to accomplish this.

- (1) The IFilterWheel property Connected is exposed in ICamera as FilterWheelConnected, and the IFilterWheel method SetupDialog() is exposed in ICamera as FilterWheelSetupDialog().

API REFERENCE

- (2) You can preface the property and method with the interface name. i.e. `IFilterWheel_Connected` and `IFilterWheel_SetupDialog()`.

In either case the net effect internally in the API is the `IFilterWheel_Connected` property delegates the call to the camera `Connected` property and the `IFilterWheel_SetupDialog()` method delegates to the camera `SetupDialog()` method. There is no need to use the filter wheel variants. They are included strictly for compatibility with the ASCOM specification.

Early Binding Notes

QSI API Release 4.5.0 exposes two new interfaces, `ICameraEx` and `IFilterWheelEx`, which inherit from `ICamera` and `IFilterWheel`. All QSI specific properties and methods (those not specified by the ASCOM specification) have been moved to the “Ex” version of each interface. Also, the `ICamera` and `IFilterWheel` interfaces have new GUIDs assigned and have been re-ordered to conform to the ASCOM V5 early binding specification.

As a result, code that was compiled with versions earlier than 4.5.0 must be recompiled after API version 4.5.0 has been installed. Any interface pointers that reference QSI specific properties and methods must be changed to the “Ex” type (i.e. `ICamera ptr`; changes to `ICameraEx ptr`). `ICameraEx` inherits from `ICamera` so that an interface pointer to `ICameraEx` has access to all of the `ICamera` methods also. The same relationship holds for `IFilterWheelEx`.

Upgrading from prior QSI API releases to release 4.5.0.

With the introduction of release 4.5.0, the typlib for the API has changed from version 2.0 to version 3.0 to accommodate the new interfaces and ASCOM dictated changes to the argument type of `ImageArray` and `ImageArrayVariant`. You must recompile any clients that were compiled for an earlier version of the API. For Microsoft Visual Studio users, a change in the typlib version requires that you re-establish the reference in your project to the new API version.

To re-establish the reference, first install the QSI API and drivers. Start Visual Studio and open the client project. In the solution explorer window, References section, delete the old reference to “`QSI Camera Lib`”. Now right click on “References” and select “Add Reference...”. Select the COM tab. Scroll down to find ASCOM Camera Driver Library for QSI Version 3.0. Select it and click OK. Now recompile the client.

API REFERENCE

Simple C++ Example

Here is a very simple example on how to use the QSI API from Visual Studio C++

```
#include "stdafx.h"
#include "stdlib.h"
#include "resource.h"
#import "progid:QSIcamera.CCDCamera"

CWinApp theApp;

using namespace std;

int _tmain(int argc, TCHAR* argv[], TCHAR* envp[])
{
    int nRetCode = 0;
    char temp[256];
    char szInfo[1024];
    QSIcameraLib::ICameraEx * pCam;

    if (!AfxWinInit(::GetModuleHandle(NULL), NULL, ::GetCommandLine(), 0))
    {
        _tprintf(_T("Fatal Error: MFC initialization failed\n"));
        return 1;
    }
    std::cout << "Hello World\n";

    HRESULT h = ::CoInitialize(NULL);

    h = ::CoCreateInstance( __uuidof (QSIcameraLib::CCDCamera), NULL,
        CLSCTX_INPROC_SERVER, __uuidof ( QSIcameraLib::ICameraEx ), (void **)
        &pCam);

    try
    {
        pCam->Connected = true;
    }
    catch (...) {return 0;}

    try
    {
        sprintf_s(szInfo, 256, "T: %5.1fC %3.0f%%\n",
            pCam->CCDTemperature, pCam->CoolerPower);
    }
    catch (...) { szInfo[0] = 0; }

    std::cout << szInfo;

    std::cin >> temp;

    try
    {
        pCam->Connected = false;
    }
    catch (...) {}

    try
    {
        pCam->Release();
    }
    catch (...) {}

    return 0;
}
```

API Reference

QSI CameraLib.CCDCamera properties and methods

Summary of Properties and Methods

Properties

ICamera

BinX	CoolerPower	LastExposureStartTime
BinY	Description	MaxADU
CameraState	DriverInfo	MaxBinX
CameraXSize	ElectronsPerADU	MaxBinY
CameraYSize	FilterOffsets	NumX
CanAbortExposure	FullWellCapacity	NumY
CanAsymmetricBin	HasShutter	PixelSizeX
CanGetCoolerPower	HeatSinkTemperature	PixelSizeY
CanPulseGuide	ImageArray	SerialNumber
CanSetCCDTemperature	ImageArrayVariant	SetCCDTemperature
CanStopExposure	ImageReady	ShutterMode
CCDTemperature	IsPulseGuiding	StartX
Connected	LastError	StartY
CoolerOn	LastExposureDuration	

ICameraEx

AntiBlooming	IsMainCamera	Name
CameraGain	LEDEnabled	PowerOfTwoBinning
FanMode	ManualShutterMode	PreExposureFlush
FlushCycles	ManualShutterOpen	ShutterPriority
HasFilterWheel	MaxExposureTime	SoundEnabled
HostTimedExposure	MinExposureTime	
ImageArrayLong	ModelNumber	

API REFERENCE

IFilterWheel

Connected
FocusOffset
Names
Position
SetupDialog

IFilterWheelEx

FilterWheelConnected
FilterWheelSetupDialog

Methods

ICamera

AbortExposure
PulseGuide
SetupDialog
StartExposure
StopExposure

ICamera Properties

AntiBlooming

Property

CCDCamera.AntiBlooming (enum AntiBloom)

Syntax

```
CCDCamera.AntiBlooming = AntiBloomingHigh;
```

Exceptions

Throws an exception if the AntiBlooming property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.AntiBlooming = AntiBloom.AntiBloomHigh
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.AntiBlooming = AntiBloom.AntiBloomHigh;
}
catch (Exception error)
{ }
```

Remarks

Controls the amount of anti-blooming in anti-blooming cameras.

Symbolic Constants

The symbolic values for AntiBloom are:

Constant	Value
AntiBloomNormal	0
AntiBloomHigh	1

BinX

Property

CCDCamera.BinX (Short)

Syntax

CCDCamera.BinX [= Short]

Exceptions

Throws an exception for illegal binning values

Examples:

VB:

```
Dim binX as Short
binX = cam.BinX
cam.BinX = 2
```

C#:

```
short binX;
binX = cam.BinX;
cam.BinX = 2;
```

Remarks

Sets the binning factor for the X axis. Also returns the current value. Defaults to 1 when the camera link is established. Note: the driver does not check for compatible sub-frame values when this value is set; rather they are checked upon StartExposure.

BinY

Property

CCDCamera.BinY (Short)

Syntax

CCDCamera.BinY [= Short]

Exceptions

Throws an exception for illegal binning values

Examples

VB:

```
Dim binY as Short
binX = cam.BinY
cam.BinY = 2
cam.BinY = cam.BinX
```

C#:

```
short binY;
binY = cam.BinY;
cam.BinY = 2;
cam.BinY = cam.BinX;
```

Remarks

Sets the binning factor for the Y axis. Also returns the current value. Defaults to 1 when the camera link is established. Note: The driver does not check for compatible sub-frame values when this value is set; rather they are checked upon StartExposure.

CameraGain

Property

CCDCamera.CameraGain (enum CameraGain)

Syntax

```
CCDCamera.CameraGain = CameraGainHigh;
```

Exceptions

Throws an exception if the CameraGain property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.CameraGain = CameraGain.CameraGainHigh
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.CameraGain = CameraGain.CameraGainHigh;
}
catch (Exception error)
{ }
```

Remarks

Controls the amount of camera gain in adjustable gain cameras. Sets the gain of the camera to maximize dynamic range. High gain is the default and provides the greatest sensitivity. Low gain is useful when binning an image where the binned pixels contain more electrons than a normal un-binned pixel. Sensitivity is lower, but the full dynamic range of the binned image can be captured. High = 0.75e-/ADU, Low = 1.5e-/ADU

Symbolic Constants

The symbolic values for CameraGain are:

Constant	Value
CameraGainHigh	0
CameraGainLow	1

CameraState

Property

CCDCamera.CameraState (read only, enumeration)

Syntax

CCDCamera.CameraState

Exceptions

Throws an exception if the camera status is unavailable.

Examples

VB:

```

If cam.CameraState = CameraState.CameraError Then
    Return
End If

```

C#:

```

if (cam.CameraState == CameraState.CameraError)
{
    return;
}

```

Remarks

Returns one of the following status information values:

Value	State	Meaning
0	CameraIdle	At idle state, available to start exposure
1	CameraWaiting	Exposure started but waiting (for shutter, trigger, filter wheel, etc.)
2	CameraExposing	Exposure currently in progress
3	CameraReading	CCD array is being read out (digitized)
4	CameraDownload	Downloading data to PC
5	CameraError	Camera error condition serious enough to prevent further operations (link fail, etc.).

CameraXSize

Property

CCDCamera.CameraXSize (read only, Long)

Syntax

CCDCamera.CameraXSize

Exceptions

Throws exception if the value is not known

Example

VB:

```
Dim x as Long  
x = cam.CameraXSize
```

C#:

```
long x;  
x = cam.CameraXSize;
```

Remarks

Returns the width of the CCD camera chip in un-binned pixels.

CameraYSize

Property

CCDCamera.CameraYSize (read only, Long)

Syntax

CCDCamera.CameraYSize

Exceptions

Throws exception if the value is not known

Examples:

VB:

```
Dim y as Long  
y = cam.CameraYSize
```

C#:

```
long y;  
y = cam.CameraYSize;
```

Remarks

Returns the height of the CCD camera chip in un-binned pixels.

CanAbortExposure

Syntax

CCDCamera.CanAbortExposure (read only, Boolean)

Syntax

CCDCamera.CanAbortExposure

Exceptions

None

Examples:

VB:

```
If cam.CanAbortExposure Then  
    cam.AbortExposure()  
End If
```

C#:

```
if (cam.CanAbortExposure)  
    cam.AbortExposure();
```

Remarks

Returns True if the camera can abort exposures; False if not.

CanAsymmetricBin

Property

CCDCamera.CanAsymmetricBin (read only, Boolean)

Syntax

CCDCamera.CanAsymmetricBin

Exceptions

Throws an exception if the value is not known.

Examples:

VB:

```
Try
    If cam.AsymmetricBin Then
        cam.BinX = 1
        cam.BinY = 2
    End If
Catch [error] As Exception
End Try
```

C#:

```
try
{
    if (cam.AsymmetricBin)
    {
        cam.BinX = 1;
        cam.BinY = 2;
    }
}
catch (Exception error)
{
}
```

Remarks

If True, the camera can have different binning on the X and Y axes, as determined by BinX and BinY. If False, the binning must be equal on the X and Y axes.

CanGetCoolerPower

Property

CCDCamera.CanGetCoolerPower (read only, Boolean)

Syntax

CCDCamera.CanGetCoolerPower

Exceptions

None

Examples:

VB:

```
If cam.CanGetCoolerPower Then  
End If
```

C#:

```
if (cam.CanGetCoolerPower)  
{  
}  
}
```

Remarks

If True, the camera's cooler set point can be adjusted. If False, the camera either uses open-loop cooling or does not have the ability to adjust temperature from software, and setting the TemperatureSetpoint property has no effect.

CanPulseGuide

Property

CCDCamera.CanPulseGuide (read only, Boolean)

Syntax

CCDCamera.CanPulseGuide

Exceptions

None

Examples:

VB:

```
If cam.CanPulseGuide Then
    cam.PulseGuide(GuideDirections.guideWest, 10)
End If
```

C#:

```
if (cam.CanPulseGuide)
{
    cam.PulseGuide(GuideDirections.guideWest, 10);
}
```

Remarks

Returns True if the camera can send auto-guider pulses to the telescope mount; False if not. (Note: this does not provide any indication of whether the auto-guider cable is actually connected.)

CanSetCCDTemperature

Property

CCDCamera.CanSetCCDTemperature (read only, Boolean)

Syntax

CCDCamera.CanSetCCDTemperature

Exceptions

None

Examples:

VB:

```
If cam.CanSetCCDTemperature Then
    cam.SetCCDTemperature (-10.7)
End If
```

C#:

```
if (cam.CanSetCCDTemperature)
{
    cam.SetCCDTemperature (-10.7);
}
```

Remarks

If True, the camera's cooler set point can be adjusted. If False, the camera either uses open-loop cooling or does not have the ability to adjust temperature from software, and setting the TemperatureSetpoint property has no effect.

CanStopExposure

Syntax

CCDCamera.CanStopExposure (read only, Boolean)

Syntax

CCDCamera.CanStopExposure

Exceptions

Throws an exception if not supported. Throws an exception if an error condition such as link failure is present.

Examples:

VB:

```
If cam.CanStopExposure Then
    cam.StopExposure()
End If
```

C#:

```
if (cam.CanStopExposure)
{
    cam.StopExposure();
}
```

Remarks

Some cameras support StopExposure, which allows the exposure to be terminated before the exposure timer completes, but will still read out the image. Returns True if StopExposure is available, False if not.

CCDTemperature

Property

CCDCamera.CCDTemperature (read only, Double)

Syntax

CCDCamera.CCDTemperature

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Dim temp as Double
temp = cam.CCDTemperature
```

C#:

```
double temp;
temp = cam.CCDTemperature;
```

Remarks

Returns the current CCD temperature in degrees Celsius. Only valid if CanControlTemperature is True.

Connected

Property

CCDCamera.Connected (Boolean)

Syntax

CCDCamera.Connected [= Boolean]

Exceptions

Throws an exception if unsuccessful.

Examples:

VB:

```
if cam.Connected = False Then
    cam.Connected = True
EndIf
```

C#:

```
if (cam.Connected == false)
    cam.Connected = true;
```

Remarks

Controls the link between the driver and the camera. Set True to enable the link. Set False to disable the link (this does not switch off the cooler). You can also read the property to check whether it is connected. The camera must be connected before using properties and methods on the camera object that relate to camera capabilities.

CoolerOn

Property

CCDCamera.CoolerOn (Boolean)

Syntax

CCDCamera.CoolerOn [= Boolean]

Exceptions

Throws an exception if not supported. Throws an exception if an error condition such as link failure is present

Examples:

VB:

```
If cam.CoolerOn = False Then
    cam.CoolerOn = True
End If
```

C#:

```
if (cam.CoolerOn == false)
    cam.CoolerOn = true;
```

Remarks

Turns on and off the camera cooler, and returns the current on/off state. Warning: turning the cooler off when the cooler is operating at high delta-T (typically >20C below ambient) may result in thermal shock. Repeated thermal shock may lead to damage to the sensor or cooler stack.

CoolerPower

Property

CCDCamera.CoolerPower (read only, Double)

Syntax

CCDCamera.CoolerPower

Exceptions

Throws an exception if not supported by the camera. Throws an exception if an error condition such as link failure is present.

Examples:

VB:

```
Dim power as Double
If cam.CoolerOn = True Then
    power = cam.CoolerPower;
End If
```

C#:

```
double power;
if (cam.CoolerOn == true)
    power = cam.CoolerPower;
```

Remarks

Returns the present cooler power level, in percent. Returns zero if CoolerOn is False.

Description

Property

CCDCamera.Description (read only, String)

Syntax

CCDCamera.Description

Exceptions

Throws an exception if description unavailable

Examples:

VB:

```
Try
    Dim desc As String
    desc = cam.Description
Catch [error] As Exception
    ' No Description available from this device
End Try
```

C#:

```
try
{
    string desc;
    desc = cam.Description;
}
Catch (Exception error)
{
    // No Description available from this device
}
```

Remarks

Returns a description of the camera model, such as manufacturer and model number. The string shall not exceed 68 characters (for compatibility with FITS headers).

DriverInfo

Property

CCDCamera.DriverInfo (read only, String)

Syntax

CCDCamera.DriverInfo

Exceptions

Throws an exception if description unavailable

Examples:

VB:

```
Try
    Dim info As String
    info = cam.DriverInfo
Catch [error] As Exception

End Try
```

C#:

```
try
{
    string info;
    info = cam.DriverInfo;
}
Catch (Exception error)
{

}
```

Remarks

Returns revision information of the loaded driver. The string shall not exceed 68 characters (for compatibility with FITS headers).

ElectronsPerADU

Property

CCDCamera.ElectronsPerADU (read only, Double)

Syntax

```
CCDCamera.ElectronsPerADU
```

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Try
  Dim epa As Double
  epa = cam.ElectronsPerADU
Catch [error] As Exception
  \ ElectronsPerADU not available from this device
End Try
```

C#:

```
try
{
  double epa;
  epa = cam.ElectronsPerADU;
}
catch (Exception error)
{
  // ElectronsPerADU not available from this device
}
```

Remarks

Returns the gain of the camera in photoelectrons per A/D unit.

EnableShutterStatusOutput

Property

QSI.Camera.EnableShutterStatusOutput (Boolean)

Syntax

```
CCDCamera.EnableShutterStatusOutput = true;
```

Exceptions

If exceptions are enabled, throws an exception if unsuccessful.

Examples:

```
bool enabled;  
enabled = cam.EnableShutterStatusOutput  
if (enabled == false)  
    cam.EnableShutterStatusOutput = true;
```

Remarks

The guider port can be configured to provide a shutter open/close indication using one of the guider port outputs. To enable this feature the property `EnableShutterStatusOutput` should be set to true. In this mode, the camera will use the the “up” output (pin 2) to reflect the shutter state. The camera will pull pin 2 to the common pin 5 while the shutter is open.

The guider ports are opto isolated open collector outputs. Each output is capable of sinking 50ma, 50 VDC maximum. The common pin must be at ground potential and the “up” output must be pulled up by an external resistor to V+.

This signal is meaningful only when the mechanical shutter is in start/stop mode (an exposure time of greater than 300 milliseconds).

To disable this feature and re-enable guiding output, set the `EnableShutterStatusOutput` property to false. The `EnableShutterStatusOutput` defaults to false on camera power up and is not saved between camera connections or power off.

FanMode

Property

CCDCamera.FanMode (enum FanMode)

Syntax

```
CCDCamera.FanMode = FanMode.FanQuiet;
```

Exceptions

Throws an exception if the FanMode property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.FanMode = FanMode.FanFull
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.FanMode = FanMode.FanFull;
}
catch (Exception error)
{
}
}
```

Remarks

Controls the speed of the camera's cooling fans.

Symbolic Constants

The symbolic values for FanMode are:

Constant	Value	Description
FanOff	0	Fans off
FanQuiet	1	Fans slow speed, full if cooling requires.
FanFull	2	Fans full speed.

FlushCycles

No longer supported. See PreExpsoureFlush.

FullWellCapacity

Property

CCDCamera.FullWellCapacity (read only, Double)

Syntax

CCDCamera.FullWellCapacity

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Try
  Dim fwc As Double
  fwc = cam.FullWellCapacity
Catch [error] As Exception
  \ FullWellCapacity not available from this device
End Try
```

C#:

```
try
{
  double fwc;
  fwc = cam.FullWellCapacity;
}
catch (Exception error)
{
  // FullWellCapacity not available from this device
}
```

Remarks

Reports the full well capacity of the camera in electrons, at the current camera settings (binning, SetupDialog settings, etc.)

HasFilterWheel

Property

CCDCamera.HasFilterWheel (read only, Boolean)

Syntax

CCDCamera.HasFilterWheel

Exceptions

Throws an exception if no camera is connected.

Examples:

VB:

```
If cam.HasFilterWheel Then  
End If
```

C#:

```
if (cam.HasFilterWheel)  
{  
}
```

Remarks

If True, the camera has an internal filter wheel. If False, the camera does not have an internal filter wheel.

HasShutter

Property

CCDCamera.HasShutter (read only, Boolean)

Syntax

CCDCamera.HasShutter

Exceptions

Throws an exception if no camera is connected.

Examples:

VB:

```
If cam.HasShutter Then  
End If
```

C#:

```
if (cam.HasShutter)  
{  
}
```

Remarks

If True, the camera has a mechanical shutter. If False, the camera does not have a shutter. If there is no shutter, the StartExposure command will ignore the Light parameter.

HeatSinkTemperature

Property

CCDCamera.HeatSinkTemperature (read only, Double)

Syntax

CCDCamera.HeatSinkTemperature

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Dim temp as Double
temp = cam.CCDTemperature
```

C#:

```
double temp;
temp = cam.CCDTemperature
```

Remarks

Returns the current heat sink temperature (The ambient air temperature as it enters that fans on the heatsink) in degrees Celsius. Only valid if CanControlTemperature is True.

HostTimedExposure

Property

CCDCamera.HostTimedExposure (read only, bool)

Syntax

```
cam. HostTimedExposure = true;
```

Exceptions

Throws an exception if the HostTimedExposure property is unsupported, if the camera is not connected, or if the command is unsuccessful.

Examples:

VB:

```
cam.HostTimedExposure = true
```

C#:

```
cam.HostTimedExpsoure = true;
```

Remarks

On Interline Transfer CCDs, like the KAI-2020M in the QSI 520i, every other column of the CCD is masked to prevent light from striking the underlying pixels. To read an image from an Interline Transfer CCD, the active pixels are transferred to the masked pixels and then shifted out of the CCD.

In normal operation, the active pixels are “flushed” at the beginning of an exposure in order to remove any charge that had built up in the pixels since the last exposure. “HostTimedExposure” mode eliminates this flush allowing you to begin integrating the next exposure while the previous exposure is being transferred to the computer.

This special mode is generally only useful when taking a rapid sequence of short exposures. If significant time is allowed to pass between exposures in this mode, dark current will likely saturate the CCD. With “HostTimedExposure” mode enabled, it is possible to take small subframes at a rate of multiple images per second, while capturing the majority of the light striking the CCD. This can be useful for some rapid guiding applications.

Note: The “Pre-Exposure Flush” options in the Advanced Dialog box are ignored when in “HostTimedExposure” mode. The only flushing that occurs in this mode is to flush the masked columns prior to transferring the image into them for reading by the computer.

ImageArray

Property

CCDCamera.ImageArray (read only, SAFEARRAY of Long)

Syntax

CCDCamera.ImageArray

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Imports System.Threading
While Not cam.ImageReady
    Thread.Sleep(100)
End While
Dim image As Array = cam.ImageArray
Dim sizeX As Integer = image.GetLength(0)
Dim sizeY As Integer = image.GetLength(1)
Dim pixel As Long = CType(image.GetValue(0, 1), Int32)
```

C#:

```
using System.Threading;
while (!cam.ImageReady) { Thread.Sleep(100); }
Array image = cam.ImageArray;
int sizeX = image.GetLength(0);
int sizeY = image.GetLength(1);
long pixel = (Int32)image.GetValue(0, 1);
```

Remarks

Returns a SAFEARRAY of Long of size NumX * NumY containing the pixel values from the last exposure. The application must inspect the SAFEARRAY parameters to determine the dimensions. Note: if NumX or NumY is changed after a call to StartExposure it will have no effect on the size of this array. This is the preferred method for programs (not scripts) to download images since it requires much less memory.

For color or multi-spectral cameras, will produce an array of NumX * NumY * NumPlanes. If the application cannot handle multi-spectral images, it should use just the first plane.

The caller must test the property ImageReady and received a true result prior to using this property, to insure that the transfer of the image from the camera is complete.

ImageArrayVariant

Property

CCDCamera.ImageArrayVariant (read only, SAFEARRAY of Variant)

Syntax

CCDCamera.ImageArrayVariant

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Imports System.Threading
While Not cam.ImageReady
    Thread.Sleep(100)
End While
Dim image As Array = cam.ImageArrayVariant
Dim sizeX As Integer = image.GetLength(0)
Dim sizeY As Integer = image.GetLength(1)
Dim pixel As Long = CType(image.GetValue(0, 1), Int32)
```

C#:

```
using System.Threading;
while (!cam.ImageReady) { Thread.Sleep(100); }
Array image = cam.ImageArrayVariant;
int sizeX = image.GetLength(0);
int sizeY = image.GetLength(1);
long pixel = (Int32)image.GetValue(0, 1);
```

Remarks

Returns a SAFEARRAY of Variant of size NumX * NumY containing the pixel values from the last exposure. The application must inspect the SAFEARRAY parameters to determine the dimensions. Note: if NumX or NumY is changed after a call to StartExposure it will have no effect on the size of this array. This property should only be used from scripts due to the extremely high memory utilization on large image arrays (26 bytes per pixel). Pixels values should be in Short, Long, or Double format.

For color or multi-spectral cameras, will produce an array of NumX * NumY * NumPlanes. If the application cannot handle multi-spectral images, it should use just the first plane.

The caller must test the property ImageReady and received a true result prior to using this property, to insure that the transfer of the image from the camera is complete.

ImageReady

Property

CCDCamera.ImageReady (read only, Boolean)

Syntax

CCDCamera.ImageReady

Exceptions

Throws an exception if hardware or communications link error has occurred.

Examples:

VB:

```
Imports System.Threading
While Not cam.ImageReady
    Thread.Sleep(100)
End While
Dim image As Array = cam.ImageArrayVariant
Dim sizeX As Integer = image.GetLength(0)
Dim sizeY As Integer = image.GetLength(1)
Dim pixel As Long = CType(image.GetValue(0, 1), Int32)
```

C#:

```
using System.Threading;
while (!cam.ImageReady) { Thread.Sleep(100); }
Array image = cam.ImageArrayVariant;
int sizeX = image.GetLength(0);
int sizeY = image.GetLength(1);
long pixel = (Int32)image.GetValue(0, 1);
```

Remarks

If True, there is an image from the camera available. If False, no image is available and attempts to use the ImageArray method will produce an exception.

IsMainCamera

Property

CCDCamera.IsMainCamera (Boolean)

Syntax

CCDCamera.IsMainCamera

Exceptions

Throws an exception if the camera is connected when attempting to set the property.

Examples:

VB:

```
Try
    Cam.IsConnected = False
    If Not cam.IsMainCamera Then
        cam.IsMainCamera = True
    End If
    Cam.IsConnected = True
Catch [error] As Exception
End Try
```

C#:

```
try
{
    Cam.IsConnected == false;
    if (!cam.IsMainCamera)
    {
        cam.IsMainCamera = true;
    }
    Cam.IsConnected = true;
}
catch (Exception error) {}
```

Remarks

If True, the camera is in the main camera role; if False, the camera is in the guider role. The camera must be in the disconnected state prior to changing the camera role (when setting this property).

IsPulseGuiding

Property

CCDCamera.IsPulseGuiding (read only, Boolean)

Syntax

CCDCamera.IsPulseGuiding

Exceptions

Throws an exception if hardware or communications link error has occurred.

Examples:

VB:

```
If cam.IsPulseGuiding Then  
End If
```

C#:

```
if (cam.IsPulseGuiding)  
{  
}
```

Remarks

If True, pulse guiding is in progress.

LastError

Property

CCDCamera.LastError (read only, String)

Syntax

CCDCamera.LastError

Exceptions

Throws an exception if no error condition.

Examples:

VB:

```
Dim error as String
error = cam.LastError
```

C#:

```
string error;
error = cam.LastError;
```

Remarks

Reports the last error condition reported by the camera hardware or communications link. The string may contain a text message or simply an error code.

LastExposureDuration

Property

CCDCamera.LastExposureDuration (read only, Double)

Syntax

CCDCamera.LastExposureDuration

Exceptions

Throws an exception if not supported or no exposure has been taken

Examples:

VB:

```
Dim time As Double
Try
    time = cam.LastExposureDuration
Catch err As Exception
End Try
```

C#:

```
double time;
try
{
    time = cam.LastExposureDuration;
}
catch( Exception err)
{

}
```

Remarks

Reports the actual exposure duration in seconds (i.e. shutter open time). This may differ from the exposure time requested due to shutter latency, camera timing precision, etc.

LastExposureStartTime

Property

CCDCamera.LastStartTime (read only, String)

Syntax

CCDCamera.LastStartTime

Exceptions

Throws an exception if not supported or no exposure has been taken.

Examples:

VB:

```
Dim time As String
Try
    time = cam.LastExposureStartTime
Catch err As Exception
End Try
```

C#:

```
string time;
try
{
    time = cam.LastExposureStartTime;
}
catch( Exception err)
{

}
```

Remarks

Reports the actual exposure start in the FITS-standard CCYY-MM-DDThh:mm:ss[.sss...] format.

LEDEnabled

Property

QSIcamera.put_LEDEnabled (Boolean)

Syntax

```
CCDCamera.LEDEnabled = true;
```

Exceptions

If exceptions are enabled, throws an exception if unsuccessful.

Examples:

```
bool enabled;  
enabled = cam.LEDEnabled;  
if (enabled == false)  
    cam.LEDEnabled = true;
```

Remarks

Enable or disable the camera status LED. The camera must be in the connected state. This setting is recorded in the system registry and will be maintained between connections to the device. This setting is unique for each device serial number.

ManualShutterMode

Property

CCDCamera.ManualShutterMode (bool ManualShutterMode)

Syntax

```
CCDCamera.ManualShutterMode = FanMode.ShutterQuiet;
```

```
bool mode = CCDCamera.ManualShutterMode;
```

Exceptions

Throws an exception if the ManualShutterMode property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.ManualShutterMode = true
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.ManualShutterMode = true;
}
catch (Exception error)
{ }
```

Remarks

Enables the manual control (using the API) of the mechanical shutter, independent of the StartExposure command. See ManualShutterOpen for further details.

ManualShutterOpen

Property

CCDCamera.ManualShutterOpen (Boolean)

Syntax

```
CCDCamera.ManualShutterOpen = true;
```

Exceptions

Throws an exception if the ManualShutterOpen property is unsupported, if the camera is not connected, if the ManualShutterMode is not enabled, or if the command is unsuccessful.

Examples:

VB:

```
Try
    cam.ManualShutterOpen = true
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.ManualShutterOpen = true;
}
catch (Exception error)
{ }
```

Remarks

Manually open (if set true) or closes (if set false) the mechanical shutter. The ManualShutterMode must be set true before issuing ManualShutterOpen commands.

MaxADU

Property

CCDCamera.MaxADU (read only, Long)

Syntax

CCDCamera.MaxADU

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Try
    Dim adu As Long
    adu = cam.MaxADU
Catch [error] As Exception

End Try
```

C#:

```
try
{
    long adu;
    adu = cam.MaxADU;
}
catch (Exception error)
{
}
```

Remarks

Reports the maximum ADU value the camera can produce.

MaxBinX

Property

CCDCamera.MaxBinX (read only, Short)

Syntax

CCDCamera.MaxBinX

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Dim maxBinX As Short  
maxBinX = cam.MaxBinX
```

C#:

```
short maxBinX;  
maxBinX = cam.MaxBinX;
```

Remarks

If `AsymmetricBinning = False`, returns the maximum allowed binning factor. If `AsymmetricBinning = True`, returns the maximum allowed binning factor for the X axis.

MaxBinY

Property

CCDCamera.MaxBinY (read only, Short)

Syntax

CCDCamera.MaxBinY

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Dim maxBinY As Short  
maxBinY = cam.MaxBinY
```

C#:

```
short maxBinY;  
maxBinY = cam.MaxBinY;
```

Remarks

If AsymmetricBinning = False, equals MaxBinX. If AsymmetricBinning = True, returns the maximum allowed binning factor for the Y axis.

MaxExposureTime

Property

CCDCamera.MaxExposureTime (read only, double)

Syntax

CCDCamera.MaxExposureTime

Exceptions

Throws an exception if data unavailable or if the camera is not connected.

Examples:

VB:

```
Dim maxExp As Double  
maxExp = cam.MaxExposureTime
```

C#:

```
double maxExp;  
maxExp = cam.MaxExposureTime;
```

Remarks

Returns the maximum exposure time in seconds for the connected camera.

MinExposureTime

Property

CCDCamera.MinExposureTime (read only, double)

Syntax

CCDCamera.MinExposureTime

Exceptions

Throws an exception if data unavailable or if the camera is not connected.

Examples:

VB:

```
Dim minExp As Double  
minExp = cam.MinExposureTime
```

C#:

```
double minExp;  
minExp = cam.MinExposureTime;
```

Remarks

Returns the minimum exposure time in seconds for the connected camera.

ModelNumber

Property

CCDCamera.ModelNumber (read only, String)

Syntax

CCDCamera.ModelNumber

Exceptions

Throws an exception if description unavailable

Examples:

VB:

```
Try
  Dim model As String
  model = cam.ModelNumber
Catch [error] As Exception

End Try
```

C#:

```
try
{
  string model;
  model = cam.ModelNumber;
}
Catch (Exception error)
{

}
```

Remarks

Returns the model number of the camera. The string shall not exceed 68 characters (for compatibility with FITS headers).

Name

Property

CCDCamera.Name (read only, String)

Syntax

CCDCamera.Name

Exceptions

Throws an exception if description unavailable

Examples:

VB:

```
Try
    Dim name As String
    name = cam.Name
Catch [error] As Exception

End Try
```

C#:

```
try
{
    string name;
    name = cam.Name;
}
Catch (Exception error)
{

}
```

Remarks

Returns the model name of the camera. The string shall not exceed 68 characters (for compatibility with FITS headers).

NumX

Property

CCDCamera.NumX (Long)

Syntax

CCDCamera.NumX [= Long]

Exceptions

None

Examples:

VB:

```
Dim numX As Long  
numX = cam.NumX
```

C#:

```
long numX;  
numX = cam.NumX;
```

Remarks

Sets the sub-frame width. Also returns the current value. If binning is active, value is in binned pixels. No error check is performed when the value is set. Defaults to CameraXSize.

NumY

Property

CCDCamera.NumY (Long)

Syntax

CCDCamera.NumY [= Long]

Exceptions

None

Examples:

VB:

```
Dim numY As Long  
numY = cam.NumY
```

C#:

```
long numY;  
numY = cam.NumY;
```

Remarks

Sets the sub-frame height. Also returns the current value. If binning is active, value is in binned pixels. No error check is performed when the value is set. Default to CameraYSize.

PixelSizeX

Property

CCDCamera.PixelSizeX(read only, Double)

Syntax

CCDCamera.PixelSizeX

Exceptions

Throws exception if data unavailable.

Examples:

VB:

```
Try
    Dim x As Double
    x = cam.PixelSizeX
Catch [error] As Exception

End Try
```

C#:

```
try
{
    double x;
    x = cam.PixelSizeX;
}
catch (Exception error)
{

}
```

Remarks

Returns the width of the CCD chip pixels in microns, as provided by the camera driver.

PixelSizeY

Property

CCDCamera.PixelSizeY(read only, Double)

Syntax

CCDCamera.PixelSizeY

Exceptions

Throws an exception if data unavailable.

Examples:

VB:

```
Try
    Dim y As Double
    y = cam.PixelSizeY
Catch [error] As Exception

End Try
```

C#:

```
try
{
    double y;
    y = cam.PixelSizeY;
}
catch (Exception error)
{

}
```

Remarks

Returns the height of the CCD chip pixels in microns, as provided by the camera driver.

PowerOfTwoBinning

Property

CCDCamera.PowerOfTwoBinning (read only, Boolean)

Syntax

CCDCamera.PowerOfTwoBinning

Exceptions

None

Examples:

VB:

```
If cam.PowerOfTwoBinning Then  
End If
```

C#:

```
if (cam.PowerOfTwoBinning)  
{  
}
```

Remarks

If True, the camera bins in powers of two. If False, the camera bins in increments of one.

PreExposureFlush

Property

CCDCamera.PreExposureFlush (enum PreExposureFlush)

Syntax

```
CCDCamera.PreExposureFlush = PreExposureFlushNormal;
```

Exceptions

Throws an exception if the PreExposureFlush property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.PreExposureFlush = PreExposureFlush.FlushNormal
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.PreExposureFlush = PreExposureFlush.FlushNormal;
}
catch (Exception error)
{ }
```

Remarks

Controls the amount of pre-exposure flushing. Flushes any previously accumulated Dark Current from the CCD imager.

None – No flushing performed. Image will contain any dark current that had accumulated since the last exposure. This mode allows for the fastest back-to-back exposures.

The next 4 modes, Modest, Normal, Aggressive and Very Aggressive, provide increasingly higher levels of flushing by employing a number of different strategies. Higher levels of flushing take more time to execute.

API REFERENCE

For KAF based cameras the flush cycles for each setting are:

None - no flush cycles
Modest - 1 flush cycle
Normal - 2 flush cycles
Aggressive - 4 flush cycles
Very Aggressive - 8 flush cycles.

Symbolic Constants

The symbolic values for PreExposureFlush are:

Constant	enum Value
FlushNone	0
FlushModest	1
FlushNormal	2
FlushAggressive	3
FlushVeryAggressive	4

SerialNumber

Property

CCDCamera.SerialNumber (read only, String)

Syntax

CCDCamera.SerialNumber

Exceptions

Throws an exception if description unavailable

Examples:

VB:

```
Try
    Dim num As String
    num = cam.SerialNumber
Catch [error] As Exception

End Try
```

C#:

```
try
{
    string num;
    num = cam.SerialNumber;
}
Catch (Exception error)
{
}
```

Remarks

Returns the serial number of the camera. The string shall not exceed 68 characters (for compatibility with FITS headers).

SetCCDTemperature

Property

CCDCamera.SetCCDTemperature (Double)

Syntax

CCDCamera.SetCCDTemperature [= Double]

Exceptions

Throws an exception if command not successful. Throws throw exception if CanSetCCDTemperature is False.

Examples:

VB:

```
Try
    Dim temp As Double
    temp = cam.SetCCDTemperature
    cam.SetCCDTemperature = 10.0
Catch [error] As Exception

End Try
```

C#:

```
try
{
    double temp;
    temp = cam.SetCCDTemperature;
    cam.SetCCDTemperature = 10.0;
}
catch (Exception error)
{

}
```

Remarks

Sets the camera cooler set-point in degrees Celsius, and returns the current set-point.

ShutterMode

No longer supported. See ShutterPriority.

ShutterPriority

Property

CCDCamera.ShutterPriority (enum ShutterPriority)

Syntax

```
CCDCamera.ShutterPriority = ShutterPriorityMechanical;
```

Exceptions

Throws an exception if the ShutterPriority property is unsupported, if the camera is not connected, or if the command is unsuccessful. This setting is stored in the system Registry and will be maintained between camera connections.

Examples:

VB:

```
Try
    cam.ShutterPriority = _
    ShutterPriority.ShutterPriorityMechanical
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.ShutterPriority = ShutterPriority.
    ShutterPriorityMechanical;
}
catch (Exception error)
{ }
```

Remarks

Controls the shutter Priority in dual shutter cameras. Only enabled when the camera has a mechanical shutter.

Mechanical – Shutter is closed between exposures and only opens for exposures that are taking an image, i.e. closed for Darks and Bias images. This mode prevents the CCD imager from being flooded with light in between exposures. This can reduce or eliminate ‘ghost’ or residual images when imaging bright objects.

Electronic – Shutter is open between exposures and only closes when taking Darks and Bias images. This mode allows the fastest back-to-back image exposures.

API REFERENCE

Symbolic Constants

The symbolic values for ShutterPriority are:

Constant	Value
ShutterPriorityMechanical	0
ShutterPriorityElectronic	1

SoundEnabled

Property

QSIcamera.put_SoundEnabled (Boolean)

Syntax

```
CCDCamera SoundEnabled = true;
```

Exceptions

If exceptions are enabled, throws an exception if unsuccessful.

Examples:

```
bool enabled;  
enabled = cam.SoundEnabled;  
if (enabled == false)  
    cam.SoundEnabled = true;
```

Remarks

Enable or disable the camera status beeper. The camera must be in the connected state. This setting is recorded in the system registry and will be maintained between connections to the device. This setting is unique for each device serial number.

StartX

Property

CCDCamera.StartX (Long)

Syntax

CCDCamera.StartX [= Long]

Exceptions

None

Examples:

VB:

```
Dim x As Long
x = cam.StartX
cam.StartX = 0
```

C#:

```
long x;
x = cam.StartX;
cam.StartX = 0;
```

Remarks

Sets the sub-frame start position for the X axis (0 based). Also returns the current value. If binning is active, value is in binned pixels.

StartY

Property

CCDCamera.StartY (Long)

Syntax

CCDCamera.StartY [= Long]

Exceptions

None

Examples:

VB:

```
Dim y As Long
y = cam.StartY
cam.StartY = 0
```

C#:

```
long y;
y = cam.StartY;
cam.StartY = 0;
```

Remarks

Sets the sub-frame start position for the Y axis (0 based). Also returns the current value. If binning is active, value is in binned pixels.

ICamera Methods

AbortExposure

Syntax

```
CCDCamera.AbortExposure()
```

Parameters

None.

Returns

Nothing

Exceptions

Throws an exception if camera is not idle and abort is unsuccessful (or not possible, e.g. during download). Throws an exception if hardware or communications error occurs.

Examples:

VB:

```
Try
    cam.AbortExposure()
Catch [error] As Exception

End Try
```

C#:

```
try
{
    cam.AbortExposure();
}
catch (Exception error)
{

}
```

Remarks

Aborts the current exposure, if any, and returns the camera to Idle state.

PulseGuide

Syntax

```
CCDCamera.PulseGuide(Direction, Duration)
```

Parameters

GuideDirections Direction - direction in which the guide-rate motion is to be made

Long Duration - Duration of the guide-rate motion (milliseconds)

Returns

Nothing.

Exceptions

Throws an exception if PulseGuide command is unsupported or the command is unsuccessful.

Examples:

VB:

```
Try
    cam.PulseGuide(GuideDirections.guideWest, 10)
Catch [error] As Exception
End Try
```

C#:

```
try
{
    cam.PulseGuide(GuideDirections.guideWest, 10);
}
catch (Exception error)
{

}
```

Remarks

This method may return immediately after the move has started, in which case back-to-back dual axis pulse-guiding can be supported. Use the IsPulseGuiding property to detect when all moves have completed.

The pulse duration resolution provided by the camera is in 10ms increments. This duration argument to this function is in millisecond increments.

API REFERENCE

Symbolic Constants

The (symbolic) values for GuideDirections are:

Constant	Value	Description
guideNorth	0	North (+ declination/elevation)
guideSouth	1	South (- declination/elevation)
guideEast	2	East (+ right ascension/azimuth)
guideWest	3	West (- right ascension/azimuth)

Note: directions are nominal and may depend on exact mount wiring.

SetupDialog

Syntax

```
CCDCamera.SetupDialog
```

Parameters

None.

Returns

Nothing.

Exceptions

Must throw an exception if Setup dialog is unavailable.

Examples:

VB:

```
cam.SetupDialog()
```

C#:

```
cam.SetupDialog();
```

Remarks

Launches a configuration dialog box for the camera. The call will not return until the user clicks OK or cancel manually. The camera Connected state must be false to change setup values for the camera.

StartExposure

Syntax

```
CCDCamera.StartExposure ( Duration, Light )
```

Parameters

Double Duration - Duration of exposure in seconds

Boolean Light - True for light frame, False for dark frame (ignored if no shutter)

Returns

Nothing.

Exceptions

Throws an exception if NumX, NumY, XBin, YBin, StartX, StartY, or Duration parameters are invalid. Throws an throw exception if CanAsymmetricBin is False and BinX < > BinY. Throws an exception if the exposure cannot be started for any reason, such as a hardware or communications error.

Examples:

VB:

```
Try  
    cam.StartExposure(1.00, True)  
Catch [error] As Exception  
End Try
```

C#:

```
try  
{  
    cam.StartExposure(1.00, true);  
}  
catch (Exception error)  
{  
  
}
```

Remarks

Starts an exposure. You must use ImageReady to check when the exposure is complete.

StopExposure

Syntax

```
CCDCamera.StopExposure()
```

Parameters

None.

Returns

Nothing.

Exceptions

Throws an exception if CanStopExposure is False. Throws an exception if no exposure is in progress. Throws an exception if the camera or link has an error condition. Throws an exception if for any reason if no image readout will be available.

Examples:

VB:

```
Try
    If cam.CanStopExposure Then
        cam.StopExposure()
    End If
Catch [error] As Exception
End Try
```

C#:

```
try
{
    if (cam.CanStopExposure)
        cam.StopExposure();
}
catch (Exception error)
{
}
}
```

Remarks

Stops the current exposure, if any. If an exposure is in progress, the readout process is initiated. Ignored if readout is already in process.

IFilterWheel Properties

Connected

Property

FilterWheel.Connected (Boolean)

Syntax

FilterWheel.Connected [= Boolean]

Exceptions

Throws an exception if connection attempt fails

Examples:

VB:

```
if cam.IFilterWheel_Connected = False Then
    cam.FilterWheel_Connected = True
EndIf
```

End If

C#:

```
if (cam.IFilter_Connected == false)
    cam.IFilterWheel_Connected = true;
```

Remarks

Controls the link between the driver and the filter wheel. Set True to enable the link. Set False to disable the link. You can also read the property to check whether it is connected. This method is provided for compatibility. Use the preferred `cam.Connected` instead (member of `ICamera`).

SetupDialog

Syntax

FilterWheel.SetupDialog

Parameters

None.

Returns

Nothing.

Exceptions

Throws an exception if no dialog box available

Examples:

VB:

```
cam.IFilterWheel_SetupDialog()
```

C#:

```
cam.IFilterWheel_SetupDialog();
```

Remarks

Launches a configuration dialog box for the driver. The call will not return until the user clicks OK or cancel manually. The dialog is the same as `cam.SetupDialog()`. This method is provided for compatibility. Use the preferred `cam.SetupDialog()` instead (member of `ICamera`).

Names

Property

FilterWheel.Names (Array of String)

Syntax

FilterWheel.Names(i)

Exceptions

Throws an exception if filter number (i) is invalid

Examples:

VB:

```
Dim name As String = CStr(cam.Names.GetValue(1))  
cam.Names.SetValue("Green", 1)
```

C#:

```
string name = (string)cam.Names.GetValue(1);  
cam.Names.SetValue("Green", 1);
```

Remarks

For each valid slot number (from 0 to N-1), reports the name given to the filter position. These names would usually be set up by the user via the SetupDialog. The number of slots N can be determined from the length of the array. If filter names are not available, then it should report back "Filter 1", "Filter 2", etc.

Position

Property

FilterWheel.Position (Short)

Syntax

FilterWheel.Position [= Short]

Exceptions

Throws an exception if filter number is invalid. Throw an exception if link error occurs.

Examples:

VB:

```
Dim pos As Short = cam.Position  
cam.Position = 2
```

C#:

```
short pos = cam.Position;  
cam.Position = 2;
```

Remarks

Write number between 0 and N-1, where N is the number of filter slots (see Filter.Names). Starts filter wheel rotation immediately when written. Reading the property gives current slot number (if wheel stationary) or -1 if wheel is moving.

FocusOffsets

Property

FilterWheel.FocusOffsets (Array of Long)

Syntax

FilterWheel.FocusOffsets(i)

Exceptions

Throws an exception if filter number (i) is invalid

Examples:

VB:

```
Dim offset As Long = CLng(cam.FocusOffset.GetValue(1))  
cam.FocusOffset.SetValue(230, 1)
```

C#:

```
long offset = (long)cam.FocusOffset.GetValue(1);  
cam.FocusOffset.SetValue(230, 1);
```

Remarks

For each valid slot number (from 0 to N-1), reports the focus offset for the given filter position. These values are focuser- and filter -dependent, and would usually be set up by the user via the SetupDialog. The number of slots N can be determined from the length of the array. If focuser offsets are not available, then it should report back 0 for all array values.

Index

- AbortExposure, 8, 16, 70
- AntiBlooming, 7, 9
- API, 0, i, 1, 2, 3, 4, 5, 7
- ASCOM, 1, 3, 4, 5
- Binning, 3
- BinX, 3, 7, 10, 11, 17, 74
- BinY, 3, 7, 11, 17, 74
- C#, 1, 2, 4, 10, 11, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 30, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 62, 63, 68, 69, 70, 71, 73, 74, 75, 76, 77, 78, 79, 80
- Camera with Filter Wheels, 3
- CameraGain, 7, 12
- cameras, 1, 21, 37, 38
- CameraState, 7, 13
- CameraXSize, 3, 7, 14, 55
- CameraYSize, 3, 7, 15, 56
- CanAbortExposure, 7, 16
- CanAsymmetricBin, 3, 7, 17, 74
- CanGetCoolerPower, 7, 18
- CanPulseGuide, 7, 19
- CanSetCCDTemperature, 7, 20, 63
- CanStopExposure, 7, 21, 75
- CCD, 0, 2, 3, 13, 14, 15, 22, 57, 58
- CCD Imager Geometry, 2
- CCDCamera, 1, 2, 4, 7, 10, 11, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30, 32, 33, 34, 35, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 62, 63, 67, 68, 69, 70, 71, 73, 74, 75
- CCDTemperature, 7, 22, 35
- COM, 0, 1, 2, 4
- Connected, 4, 5, 7, 8, 23, 29, 45, 67, 73, 76
- CoolerOn, 7, 24, 25
- CoolerPower, 7, 25
- Description, 7, 9, 12, 26, 30, 61, 66, 72
- DriverInfo, 7, 27
- ElectronsPerADU, 4, 7, 28
- EnableShutterStatusOutput, 29
- FanMode, 7, 30
- Filter Wheels, 1, 3
- FilterOffsets, 7
- FlushCycles, 31
- FocusOffsets, 80
- FullWellCapacity, 7, 32
- geometry, 2
- HasFilterWheel, 3, 4, 7, 33
- HasShutter, 3, 7, 34
- HeatSinkTemperature, 7, 35
- HostTimedExposure, 7, 36
- Image copy efficiency, 3
- ImageArray, 3, 7, 37, 39
- ImageArrayVariant, 4, 7, 38, 39
- ImageReady, 7, 37, 38, 39, 74
- Imports, 2, 37, 38, 39
- installation disc, 1
- interface, 1, 4, 5
- Introduction, 1
- IsMainCamera, 40
- IsPulseGuiding, 7, 40, 41, 71
- LastError, 7, 42
- LastExposureDuration, 7, 43
- LastExposureStartTime, 7, 44
- LEDEnabled, 7
- ManualShutterMode, 7
- ManualShutterOpen, 7
- MaxADU, 7, 48
- MaxBinX, 7, 49, 50
- MaxBinY, 7, 50
- MaxExposureTime, 7, 51
- Microsoft, 1
- MinExposureTime, 52
- ModelNumber, 53
- MS Office, 1
- Name, 54
- Names, 8, 78, 79
- NumX, 3, 7, 37, 38, 55, 74
- NumY, 3, 7, 37, 38, 56, 74
- PixelSizeX, 7, 57
- PixelSizeY, 7, 8, 58
- Position, 79
- PowerOfTwoBinning, 7, 59
- PreExposureF'ush, 7
- ProgID, 2
- PulseGuide, 8, 19, 30, 46, 47, 71
- QSI, i, 1, 2, 3
- QSIcamera.dll, 1
- QSIcameraLib, 2, 7
- Regsvr32.exe, 1
- SAFEARRAY, 3
- Sample C# Program, 80
- SerialNumber, 7, 62
- SetCCDTemperature, 1, 7, 20, 63
- SetupDialog, 4, 5, 8, 32, 73, 77, 78, 80
- Shutter Mode, 7
- Shutter-less Cameras, 3
- ShutterMode, 46, 47, 64
- ShutterPriority, 7, 36, 64, 65, 66
- SoundEnabled, 67
- StartExposure, 3, 8, 10, 11, 34, 37, 38, 74
- StartX, 3, 7, 68, 74
- StartY, 3, 7, 69, 74
- StopExposure, 8, 21, 75
- Supporting Information, 2
- try/catch, 4
- using, 2, 3, 23, 37, 38, 39
- VB.net, 1
- VBA, 1
- VBScript, 1
- VBScript, 4

